

Multiple Output Linear D.C. Power Supply



The GPE-X323 series is cutting edge, economical linear DC Power supplies. The GPE-X323 series features output power from 192 to 217 watts, three independent isolated output channels (for GPE-3323), high resolution, low noise, high reliability, and compact size. The GPE-X323 series has a built-in digital panel control design to replace conventional control method. This unique design allows the GPE-X323 series linear DC power supply to provide users with more efficient functionalities, including set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage and current parameters. Additionally, output key light facilitates users in clearly reading the operational status of power supply.

High Resolution

The GPE-X323 series features 10mV/1mA high resolution (for setting and read back). The series outputs a pure and stable power supply. Users can easily simulate small voltage or small current measurements for DUTs that is the area the conventional low resolution linear power supplies can't achieve.



4.3 Inch LCD display provide high resolution for 10mV/1mA.

Convenient Function

The GPE-X323 series has a built-in set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage/current parameters.



The key lock function prevent DUTs from unnecessary damages caused by mis-operation.

Tracking Series and Parallel Operation

In addition to independent output channels, the GPE-X323 series provides tracking series and parallel operation (For GPE-2323/GPE-3323/GPE-4323). The series and parallel connections allow power supplies to output 32V/6A (Parallel Connection) and 64V/3A (Series Connection).



Internal connection for tracking Series and Parallel operation via control panel

Remote I/O for output On/Off function

The GPE-X323 Series also provides the analog control (Remote I/O) function for external output On/Off control.



For controlling the output On/Off function through the specific pin assignment of remote control connector which is in rear panel.

GPE-X323 Series

FEATURES

- 1/2/3/4 Independent Isolated Output
- 4.3 Inch LCD Display
- Setting & Read Back Resolution 10mV/1mA
- Output On/off
- Analog Control (Remote I/O) For Output ON/OFF
- Set View Function For Checking an Original V/I Setting During Output On
- Key Lock Function
- Tracking Series And Parallel Operation
- Smart Cooling Fan Achieving Low Noise
- Optional European Jack Type Terminal



Front



Rear Panel

APPLICATIONS

- Laboratories and Educational Facilities
- Product Testing and Quality Assurance
- Service Operation and Post-Sales Support
- Product Development and Debugging

SPECIFICATIONS

		GPE-4323				GPE-3323			GPE-2323		GPE-1326	
OUTPUT MODE	Number of Channel	CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH1	CH2	CH1	
	Voltage	0~32V	0~32V	0~5V	0~15V	0~32V	0~32V	5V	0~32V	0~32V	0~32V	
CONSTANT VOLTAGE OPERATION	Current	0~3A	0~3A	0~1A	0~1A	0~3A	0~3A	5A	0~3A	0~3A	0~6A	
	Tracking Series Voltage	0~64V	-	-	-	0~64V	-	-	0~64V	-	-	
CONSTANT CURRENT OPERATION	Tracking Parallel Current	0~6A	-	-	-	0~6A	-	-	0~6A	-	-	
	Line Regulation	$\leq 0.01\% + 3mV$			Load Regulation	$\leq 0.01\% + 3mV$ (rating current $\leq 3A$) ; $\leq 0.02\% + 5mV$ (rating current $> 3A$)			Ripple & Noise	$\leq 1mVRms(5Hz \sim 1MHz)$		
TRACKING OPERATION (CH1,CH2)	Recovery Time	$\leq 100\mu s$ (50% Load Change, minimum load 0.5A)			Line Regulation	$\leq 0.2\% + 3mA$			Load Regulation	$\leq 0.2\% + 3mA$		
	Series Regulation	$\leq 0.2\% + 3mA$			Ripple & Noise	$\leq 3mA_{RMS}$			Parallel Regulation	$\leq 0.1\% + 10mV$ of Master (0~32V) No Load , with Load add load regulation $\leq 100mV$		
CH3 OPERATION FOR (GPE-3323)	Line Regulation	Line : $\leq 0.01\% + 3mV$			Load Regulation	Load : $\leq 0.01\% + 3mV$ (rating current $\leq 3A$) ; $\leq 0.02\% + 5mV$ (rating current $> 3A$)			Ripple & Noise	Line : $\leq 0.01\% + 5mV$		
	Load Regulation	Load : $\leq 100mV$			Ripple & Noise	$\leq 1mVRms(5Hz \sim 1MHz)$			Output Voltage	5.0V, $\pm 5\%$		
METER	Output Current	5A			Line Regulation	$\leq 3mV$			Load Regulation	$\leq 5mV$		
	Setting Accuracy	$\leq 5mV$			Ripple & Noise	1mVRms(5Hz~1MHz)			Output Current	$\leq 5A$		
INSULATION	Voltage Resolution	10mV			Current Resolution	1mA			Setting Accuracy	Voltage : $\pm 0.1\%$ of reading +30mV; Currents : $\pm 0.3\%$ of reading +6mA		
	Setting Accuracy	Voltage : $\pm 0.1\%$ of reading +30mV; Currents : $\pm 0.3\%$ of reading +6mA			Readback Accuracy	Voltage : $\pm 0.1\%$ of reading +30mV; Currents : $\pm 0.3\%$ of reading +6mA			Readback Accuracy	Voltage : $\pm 0.1\%$ of reading +30mV; Currents : $\pm 0.3\%$ of reading +6mA		
ENVIRONMENT CONDITION	Chassis and Terminal	20MΩ or above (DC 500V)			Chassis and AC Cord	30MΩ or above (DC 500V)			Operation Temp	0~40°C		
	Storage Temp	-10~70°C			Operating Humidity	$\leq 80\%$ RH			Storage Humidity	$\leq 70\%$ RH		
OTHER	Power Source	AC100V/120V/220V±10%; 230V(+10%~-6%); 50/60Hz			Dimensions & Weight	210(W)x155(H)x306(D) mm ; Approx. 7kg						

Specifications subject to change without notice.

PE-1326CD1DH

ORDERING INFORMATION

GPE-1326 Single Channel, 192W Linear DC Power Supply

GPE-2323 2 Channels, 192W Linear DC Power Supply

GPE-3323 3 Channels, 217W Linear DC Power Supply

GPE-4323 4 Channels, 212W Linear DC Power Supply

ACCESSORIES

User Manual (CD) x 1 ; Power Cord x 1

GPE-1326 Test Lead GTL-104 x 1; GTL-105 x 1; or European GTL-204A x 1, GTL-203A x 1

GPE-2323 Test Lead GTL-104 x 2; or European GTL-204A x 2,

GPE-3323 Test Lead GTL-104 x 3; or European GTL-204A x 3

GPE-4323 Test Lead GTL-104 x 2; GTL-105 x 2 or European GTL-204A x 2, GTL-203A x 2

Global Headquarters

GOOD WILL INSTRUMENT CO., LTD.

No.731, Jengjung Road, Tucheng Dist., New Taipei City 236, Taiwan
T +886-2-2268-0389 F +886-2-2268-0639

E-mail: marketing@goodwill.com.tw

China Subsidiary

GOOD WILL INSTRUMENT (SUZHOU) CO., LTD.

No. 521, Zhujiang Road, Sudi, Suzhou Jiangsu 215011 China
T +86-512-8661-7177 F +86-512-6661-7277

E-mail: marketing@imtek.com.cn

Malaysia Subsidiary

GOOD WILL INSTRUMENT (M) SDN. BHD.

27, Persiaran Mahsuri 1/1, Sunway Tunas,
11900 Bayan Lepas, Penang, Malaysia
T +604-6399988 F +604-6309583

E-mail: sales@goodwill.com.my

Europe Subsidiary

GOOD WILL INSTRUMENT EURO B.V.

De Rui 5427A, 3584DC Veldhoven, THE NETHERLANDS
T +31(0)40-2537790 F +31(0)40-2541194

U.S.A. Subsidiary

INSTEK AMERICA CORP.

5190 Brooks Street Montclair, CA 91763, U.S.A.
T +1-909-399-3535 F +1-909-399-0819

E-mail: Sales@instekamerica.com

Japan Subsidiary

TEXIO TECHNOLOGY CORPORATION.

7F Towa Fudosan Shin Yokohama Bldg., 2-18-13 Shin
Yokohama, Kohoku-ku, Yokohama, Kanagawa,
222-0033 Japan

T +81-45-620-2305 F +81-45-534-2181

E-mail: info@texio.co.jp

Korea Subsidiary

GOOD WILL INSTRUMENT KOREA CO., LTD.

#1406, Aca HighTech-City B/D 1Dong,
Mulse-Dong 3Ga 55-20, Yeongdeungpo-Gu, Seoul, Korea
T +82-2-3439-2205 F +82-2-3439-2207

E-mail: gwmstek@gwmstek.co.kr

GW INSTEK

Simply Reliable



www.gwmstek.com

www.facebook.com/GWINSTEK